

CPSC 213

Introduction to Computer Systems

Unit 1d

Static Control Flow

Readings for Next 2 Lectures

- ▶ Textbook
 - Condition Codes - Loops
 - 3.6.1-3.6.5

```
int s=0;
int i;
int a[] = {2,4,6,8,10,12,14,16,18,20};

void foo () {
  for (i=0; i<10; i++)
    s += a[i];
}
```

Using array syntax

- ▶ Using pointer-arithmetic syntax for access to a?
- ▶ Will this technique generalize
 - will it work for all loops? why or why not?

Control Flow

- ▶ The flow of control is
 - the sequence of instruction executions performed by a program
 - every program execution can be described by such a linear sequence
- ▶ Controlling flow in languages like Java

Loops (S5-loop)

```
public class Foo {
  static int s = 0;
  static int i;
  static int a[] = new int[10];

  static void foo () {
    for (i=0; i<10; i++)
      s += a[i];
  }
}

int s=0;
int i;
int a[] = {2,4,6,8,10,12,14,16,18,20};

void foo () {
  for (i=0; i<10; i++)
    s += a[i];
}
```

In C

Implement loops in machine

```
int s=0;
int i;
int a[] = {2,4,6,8,10,12,14,16,18,20};

void foo () {
  for (i=0; i<10; i++)
    s += a[i];
}
```

- ▶ Can we implement **this** loop with the existing ISA?

Loop unrolling

Using array syntax

```
int s=0;
int i;
int a[10] = {2,4,6,8,10,12,14,16,18,20};

void foo () {
  i = 0;
  s += a[i];
  i++;

  s += a[i];
  i++;

  ...

  s += a[i];
  i++;
}
```

- ▶ Using pointer-arithmetic syntax for access to a?
- ▶ Will this technique generalize
 - will it work for all loops? why or why not?

Control-Flow ISA Extensions

- ▶ Conditional branches
 - goto <address> if <condition>
- ▶ Options for evaluating condition
 - unconditional
 - conditional based on value of a register (==0, >0 etc.)
 - goto <address> if <register> <condition> 0
 - conditional check result of last executed ALU instruction
 - goto <address> if last ALU result <condition> 0
- ▶ Specifying target address
 - absolute 32-bit address
 - this requires a 6 byte instruction, which means jumps have high overhead
 - is this a serious problem? how would you decide?
 - are jumps for for/while/if etc. different from jumps for procedure call?

PC Relative Addressing

- ▶ Motivation
 - jumps are common and so we want to make them as fast as possible
 - small instructions are faster than large ones, so make some jumps be two bytes
- ▶ Observation
 - some jumps such as for/while/if etc. normally jump to a nearby instruction
 - so the jump distance can be described by a small number that could fit in a byte
- ▶ PC Relative Addressing
 - specifies jump target as a delta from address of current instruction (actually next)
 - in the execute stage **pc register** stores the address of next sequential instruction
 - the pc-relative jump delta is applied to the value of the pc register
 - jumping with a delta of 0 jumps to the next instruction
 - jump instructions that use pc-relative addressing are called **branches**
- ▶ Absolute Addressing
 - specifies jump target using full 32-bit address
 - use when the jump distance too large to fit in a byte

ISA for Static Control Flow (part 1)

- ▶ ISA requirement (apparently)
 - at least one PC-relative jump
 - specify relative distance using real distance / 2 — why?
 - at least one absolute jump
 - some conditional jumps (at least = and > 0)
 - make these PC-relative — why?
- ▶ New instructions (so far)

Name	Semantics	Assembly	Machine
branch	pc ← (a==pc+oo*2)	br a	8-oo
branch if equal	pc ← (a==pc+oo*2) if r[c]==0	beq rc, a	9coo
branch if greater	pc ← (a==pc+oo*2) if r[c]>0	bgt rc, a	acoo
jump	pc ← a	j a	b--- aaaaaaa

Implementing for loops (S5-loop)

```
for (i=0; i<10; i++)
  s += a[i];
```

General form

- in C and Java

```
for (<init>; <continue-condition>; <step>) <statement-block>
```

- pseudo-code template

```
<init>
loop: goto end_loop if not <continue-condition>
<statement-block>
<step>
goto loop
end_loop:
```

This example

- pseudo code template

```
i=0
loop: goto end_loop if not (i<10)
s+=a[i]
i++
goto loop
end_loop:
```

- ISA suggests two transformations

- only conditional branches we have compared to 0, not 10
- no need to store i and s in memory in each loop iteration, so use temp_ to indicate this

```
temp_i=0
temp_s=0
loop: temp_t=temp_i-10
goto end_loop if temp_t==0
temp_s+=a[temp_i]
temp_i++
goto loop
end_loop: s=temp_s
i=temp_i
```

```
temp_i=0
temp_s=0
loop: temp_t=temp_i-10
goto end_loop if temp_t==0
temp_s+=a[temp_i]
temp_i++
goto loop
end_loop: s=temp_s
i=temp_i
```

- assembly code Assume that all variables are global variables

```
ld $0x0, r0 # r0 = temp_i = 0
ld $a, r1 # r1 = address of a[0]
ld $0x0, r2 # r2 = temp_s = 0
ld $0xfffffff6, r4 # r4 = -10
loop: mov r0, r5 # r5 = temp_i
add r4, r5 # r5 = temp_i-10
beq r5, end_loop # if temp_i=10 goto +4
ld (r1, r0, 4), r3 # r3 = a[temp_i]
add r3, r2 # temp_s += a[temp_i]
inc r0 # temp_i++
br loop # goto -7
end_loop: ld $s, r1 # r1 = address of s
st r2, 0x0(r1) # s = temp_s
st r0, 0x4(r1) # i = temp_i
```

Implementing if-then-else (S6-if)

```
if (a>b)
  max = a;
else
  max = b;
```

General form

- in Java and C
 - if <condition> <then-statements> else <else-statements>
- pseudo-code template

```
temp_c = not <condition>
goto then if (temp_c==0)
else: <else-statements>
goto end_if
then: <then-statements>
end_if:
```

This example

- pseudo-code template

```
temp_a=a
temp_b=b
temp_c=temp_a-temp_b
goto then if (temp_c>0)
else: temp_max=temp_b
goto end_if
then: temp_max=temp_a
end_if: max=temp_max
```

- assembly code

```
ld $a, r0 # r0 = &a
ld 0x0(r0), r0 # r0 = a
ld $b, r1 # r1 = &b
ld 0x0(r1), r1 # r1 = b
mov r1, r2 # r2 = b
not r2 # temp_c = ! b
inc r2 # temp_c = - b
add r0, r2 # temp_c = a-b
bgt r2, then # if (a>b) goto +2
else: mov r1, r3 # temp_max = b
br end_if # goto +1
then: mov r0, r3 # temp_max = a
end_if: ld $max, r0 # r0 = &max
st r3, 0x0(r0) # max = temp_max
```

Static Procedure Calls

Code Examples (S6-static-call)

```
public class A {
  static void ping () {}
}

public class Foo {
  static void foo () {
    A.ping ();
  }
}
```

```
void ping () {}

void foo () {
  ping ();
}
```

Java

- a **method** is a sub-routine with a name, arguments and local scope
- method **invocation** causes the sub-routine to run with values bound to arguments and with a possible result bound to the invocation

C

- a **procedure** is ...
- a procedure **call** is ...

Diagramming a Procedure Call

```
void foo () {
  ping ();
}
```

```
void ping () {}
```

Caller

- goto ping
- j ping
- continue executing

Callee

- do whatever ping does
- goto foo just after call to ping()
- ??????

Questions

How is RETURN implemented?
It's a jump, but is the address a static property or a dynamic one?

17

Implementing Procedure Return

return address is

- the address the procedure jumps to when it completes
- the address of the instruction following the call that caused it to run
- a dynamic property of the program

questions

- how does procedure know the return address?
- how does it jump to a dynamic address?

18

saving the return address

- only the caller knows the address
- so the caller must save it before it makes the call
 - caller will save the return address in **r6**
 - there is a bit of a problem here if the callee makes a procedure call, more later ...
- we need a new instruction to read the PC
 - we'll call it gpc

jumping back to return address

- we need new instruction to jump to an address stored in a register
 - callee can assume return address is in r6

ISA for Static Control Flow (part 2)

New requirements

- read the value of the PC
- jump to a dynamically determined target address

Complete new set of instructions

Name	Semantics	Assembly	Machine
<i>branch</i>	$pc \leftarrow (a == pc + oo * 2)$	br a	8-oo
<i>branch if equal</i>	$pc \leftarrow (a == pc + oo * 2)$ if $r[c] == 0$	beq a	9coo
<i>branch if greater</i>	$pc \leftarrow (a == pc + oo * 2)$ if $r[c] > 0$	bgt a	acoo
<i>jump</i>	$pc \leftarrow a$	j a	b--- aaaaaaa
<i>get pc</i>	$r[d] \leftarrow pc$	gpc rd	6f-d
<i>indirect jump</i>	$pc \leftarrow r[t] + (o == pp * 2)$	j o(rt)	ctpp

20

Compiling Procedure Call / Return

```
void foo () {
  ping ();
}
```

```
foo: ld $ping, r0 # r0 = address of ping ()
     gpc r6 # r6 = pc of next instruction
     inca r6 # r6 = pc + 4
     j (r0) # goto ping ()
```

```
void ping () {}
```

```
ping: j (r6) # return
```

21